

AURA

2G AND 3G READY
COMPLETE CELLULAR BOOSTER KIT

Product Number: (CA-VAT)

The AURA 2G/3G Cellular Booster Kit is our entry-level marine kit that enhances virtually all US Carriers' 2G and 3G voice and data service. The AURA supports 7+ simultaneous users and a wide coverage area with clear calls and reliable service. Independently adjustable antenna balancing dial controls allow the user to adjust the boost for pinpoint signal enhancement. The AURA is backed by an industry-leading 3 Year manufacturer's warranty.



Kit Includes: (pictured items)
 • CA-VAT Amplifier • Outdoor Antenna • Indoor Antenna
 • Coax Cable • Antenna Ferrule • Antenna Mount • User Manual

Features:

- Dual-Band Booster
- Dual Embedded CPU's
- Automatic Shutdown
- Stealth Technology Incorporated
- Fully Marineized Metal Casing
- Fully Plug and Play
- FCC Certified

Benefits:

- Boosts 2G And 3G Signals on All Major US Cellular Networks
- Independently Reconfigurable For Each Band For Best Possible Performance
- Built-In Safeguards Completely Eliminate Interference To Cell Tower
- Uplink Becomes Dormant When Not in Use, Saving Power
- Durable Protection From The Elements, Designed For Marine Use
- Simple, Intuitive Set-Up And Operation
- Completely Legal And FCC Certified For New Rigid Protection Standards



Easy Set Up

Energy Efficient and Durable

Increase Reception = MORE BARS

Improves Cell Battery Life

TECHNICAL SPECIFICATIONS

Product Number: CA- VAT

Frequency	Uplink 824-849/1850-1910MHz Downlink: 869-894/1930-1990 MHz
Input Impedance	50 ohm
Maximum Gain	50dB
VSWR	≤2.0
Standard Supported	CDMA, GSM, WCDMA, HSPA(+), EVDO, EDGE and all other standard cellular standards
Power Supply	AC: 110V, 60Hz; DC: 5-15V
Maximum RF Output Power	1watt EIRP
Noise Figure	5dB
RF connectors	FME-Female Booster, N-Male Antenna
Power Consumption	<10W
Dimensions	8in x 1.25in x 5in
Amplifier Weight	1lb 8oz
FCC ID (USA)	RSNFLEX2GO

*Non-carrier specific. Works in the US and Canada